

PRODUCT TECHNICAL DATASHEET

B71/BC/INT



CODE	DESCRIPTION	PCS/PALLET
B71/BC/INT	Kit for emergency batteries charger for Brushless digital controller 24V DC with plug-in cord, with 2 recovery batteries 12V DC, 1,2 Ah. Box case included.	

PRODUCT TECHNICAL SPECIFICATIONS	
Power line supply	16V AC ... 24V AC
Operating temperature	-20°C +55°C
Maximum input power	15W
Lead-acid batteries	2 x 12V DC 1200mAh, connected in series (external B71/B)
Nominal charge voltage	27.6 V DC
Minimum self-protection voltage of battery	19.5 V DC
"br" open jumper charge current	250 mA (for 1200mah batteries)
"br" close jumper charge current	400 mA (optional, for fast charge of 4500mAh batteries) - B71/BC/EXT
Maximum dimension product in mm (L x W x H)	243 x 49 x 89
Product weight packed (Kg)	1.5

PRODUCT ACCESSORIES

Batteries, Chargers and
Inverter